Product information	Partners or other established bra	e same type and rating, available from John Lewis	JOHN LEWIS & PARTNERS	obi 4 light User guide	SPOTLIGHT	BAR
Aftercare and Troubleshooting	You've switched on the light, but it's not working: 1. Check your power supply is switched on 2. Turn off the light and check that the bulb is inserted correctly 3. Check the bulb is still in working order					
		product that you can't solve, please contact your or call Technical Support on 03301 230106.				
Specification	Max power: 4 x 7W Recommended bulb: 7W LED GU10 bulb for maximum brightness. Lower wattages are also suitable. Rated input: 220 –240V, 50Hz Bulbs not included IP rating: 20 Weight: 1.6kg	Fitting a GU10 bulb Fit bulb pins into round holes. Then twist clockwise to lock. Ensure the bulb fitting tool is clean prior to fitting the bulb. Any traces of dust can be wiped away with a damp cloth.				
5-year guarantee	At John Lewis & Partners we test every light to high quality standards. That means we can offer you a 5-year guarantee.					
Recycling	This symbol 🔏 indicates that this product should not be treated as normal household waste and it should be recycled. John Lewis & Partners do not operate instore take back, but as members of the Distributor Take Back scheme have funded the development and upgrade of recycling facilities across the UK. Please take it to your nearest collection facility or for further details contact your local council or visit www.recycle-more.co.uk.					
			5			

15/10/2024

John Lewis plc SW1V 2QQ johnlewis.com

Made in China

Please retain these instructions for future reference.

5 YEARS

Product Code: 10522203

Getting started	Thank you for purchasing this John Lewis & Partners product. For your safety, and to make sure everything is working properly, please read the instructions	Product assem	
	carefully before use.	Step 1 Carefully unpack th	
Warnings	This is a Class 1 product and must be earthed. It is recommended that this fitting is installed by a qualified electrician.	are present before fitting, carefully no	
	Install in accordance with the IEE Wiring regulations and the Building Regulations. To prevent electrocution switch off at mains supply before installing or maintaining this fitting. Ensure other persons cannot restore the electrical supply without your knowledge.	Step 2 Remove the fixing loosening the two	
	If you are in any doubt, please consult a qualified electrician. This light fitting should be connected to a 5 amp fused circuit. If replacing an existing fitting, make a note of the connections. Always use the correct type and wattage bulb. Never exceed the wattage stated. Dispose of used bulbs carefully. GU10 LED bulbs up to 7W can be used - but ensure that the minimum distance to the illuminated surface is not less than 0.5m (50 cm).	Ensure there is a so of the light fitting. the position of the rotation of the proc wall plugs (C) (sui avoid damaging an	
	This product is suitable for installation on surfaces with normal flammability e.g. wood, plasterboard, masonry. It is not suitable for use on highly flammable surfaces	Fix the bracket to t	
	(e.g. polystyrene, textiles). For your safety, always switch off the supply and allow the fitting to cool down	Step 3 Having identified th	

before changing lightbulbs, cleaning or adjusting heads.

Parts list

Description	Image	Quantity
Light fitting		× 1
Bulb fitting tool		x 1
Wall plugs		x 2
Screws	(fannunnes- (fannunnes-	x 2

nbly

the carton, making sure all the parts re assembly. Before removing the existing ote the position of each set of wires.

ng bracket (A) from the product by vo side screws (B).

solid mounting surface to support the weight . Using the fixing bracket as a template, mark ne mounting holes. Take into account the slight oduct in step 4. Drill holes and fit supplied uitable for masonary only). Take care to any concealed wiring and pipes.


the ceiling using supplied screws (D).

the household wiring from your existing light fitting, connect to the connection block inside the product in the following way (E). Check that: You have correctly identified the house wires. The connections are tight. No loose strands have been left out of the

connection block.

Step 4

This product has "L" shaped fixing slots to allow easy fixing to the fixing bracket. Locate the "L" slots (F) around the small screws (B) on the fixing bracket (A). Rotate the ceiling cover to attach the product to the bracket. Tighten the screws to secure. Take care not to trap any wiring.



 \bigcirc \bigcirc

 \otimes \otimes

 \otimes \otimes

0

HOUSEHOLD SUPPLY

NEUTRAL

EARTH

SWITCHED LIVE

Step 5


Using the supplied tool (G) fit the recommended bulbs (H) as per the details overleaf.


Step 6

Your light is now ready for use.

Note:

The angle of the heads can be adjusted to the appropriate angle as needed.





LIGHT FITTING

BLUE (N)

GREEN/YELLOW

CONNECTION

BROWN (L)